

19"-MODULAR PRE-AMPLIFIER (for up to 2 modules)



Description

The module carrier ME-1A offers in just one rack unit, the possibility to mount up to two audio modules, to save space. The modules of the AM-Series can be combined as necessary depending on.

On the back there is a L/R output per module and an additional output priority. The signal from the built-in module 2 (on the right side) has output priority. Ends the playback of this module, it automatically switched to module 1.

A 75 ohm antenna input and the 24V DC input complete the multi-purpose device.

Please consider the following features:

- The ME-1 A has a priority output.

The device operates on 230 V AC mains power and 24 V DC (emergency power supply).

- Suitable for 19" mounting or table top.

★

RDS Tuner
10 FM/10 AM station memory



AM-100 RDS

DAB-Tuner BT/USB/SD
Player with Remote control



AM-100 DAB

DVD/CD/USB/SD-Player
with Remote control



AM-100 DV

CD/USB/SD-Player
with Pitch-, Remote control and Aux



AM-201 CD

BT-Player-Modul
USB-Port/SD-Card, Remote control



AM-100 BT

Technical data	ME-1 A
Module slots	2
Outputs	Stereo Cinch channel 1; Stereo Cinch channel 2; Stereo Cinch priority
Inputs	75 ohms coaxial antenna; draft antenna; Record In Stereo Cinch
Power supply	230 V power supply; 24 V DC
Scope of supply	Module carrier ME-1 A, 3 pcs. audio cable Cinch, power supply cable
Dimensions (WxHxD)	483 x 43 x 295 mm, 1 RU
Weight	2,8 kg

Model designation

Modular pre-amplifier, (1 RU) ME-1 A